




SUGGESTED SURFACE MOUNTING FOR COMMERCIAL HID LITES

Series S8-V7


SURFACE

1. Remove lens frame assembly by loosening all captive screws.
2. Squeeze the two (2) safety wire hinges or unclip the two (2) safety snells, whichever is being used.
3. Remove the reflector and ballast cover by turning the quarter-turn fasteners.
4. Mount luminaire to ceiling utilizing four (4) mounting holes provided.
5. Make all necessary wiring and connections.
6. Replace ballast cover, reflector, install lamp, safety wire hinges or safety snells and lens assembly.




PENDANT

1. Remove lens frame assembly by loosening all captive screws.
2. Squeeze the two (2) safety wire hinges or unclip the two (2) safety snells, whichever is being used.
3. Remove the reflector and ballast cover by turning the quarter-turn fasteners.
4. Secure pendant to luminaire and properly seal.
5. Make all necessary electrical connections to supply wires brought through pendant.
6. Replace ballast cover, reflector, install lamp, safety wire hinges or safety snells and lens assembly.



CHAIN

1. Remove lens frame assembly by loosening all captive screws.
2. Squeeze the two (2) safety wire hinges or unclip the two (2) safety snells, whichever is being used.
3. Remove the reflector and ballast cover by turning the quarter-turn fasteners.
4. Mount four (4) 1-1/2" spacing brackets to holes in back of luminaire (see instructions in mounting kit).
5. Insert "S" hooks in holes in mounting brackets, hang from chain, close hooks.
6. Make all necessary wiring and connections.
7. Replace ballast cover, reflector, install lamp, safety wire hinges or safety snells and lens assembly.



Cardboard lampholder guard must be removed prior to lamping.

Cleaning Instructions: Wipe luminaire with a soft cloth slightly dampened with warm, soapy water. On stainless steel units, tightly adhering deposits may be removed by using a stainless steel polishing powder. Never use steel wool or steel brushes on stainless steel. Always rub in the directions of the polish lines.

Note: All luminaires to be installed by a qualified electrician.
Mounting and electrical hardware not supplied by Paramount Industries unless otherwise noted.